

Wireless Channel Estimation with Low-Complexity 1-bit ADC and Unknown Quantization Threshold

Manuel S. Stein, Shahar Bar, Josef A. Nossek, and Joseph Tabrikian

Abstract—In this paper, the problem of signal parameter estimation from measurements acquired by a low-complexity analog-to-digital converter (ADC) with 1-bit output resolution and an unknown quantization threshold is considered. Single-comparator ADCs are energy-efficient and can be operated at ultra-high sampling rates. For analysis of such hard-limiting systems, a fixed and known quantization threshold is usually assumed. In the symmetric case, i.e., zero hard-limiting offset, it is well-understood that in the low signal-to-noise ratio (SNR) regime the signal processing performance degrades moderately by $2/\pi$ (−1.96 dB) when comparing to an ideal ∞ -bit converter. Due to hardware imperfections, low-complexity 1-bit ADCs will in practice exhibit an unknown threshold different from zero. Therefore, the offset has to be estimated jointly with the signal parameters. Here we study the estimation accuracy which can be obtained with receive data preprocessed by a hard-limiter with unknown quantization level. In order to characterize the achievable performance, we employ analytic error expressions for different setups while modeling the offset as a nuisance parameter. In the low SNR regime we establish the necessary condition for a vanishing loss due to missing offset knowledge at a receiver with 1-bit ADC. We then validate our analysis by visualizing the quantization loss under an unknown 1-bit threshold when wireless intersymbol interference (ISI) channel estimation is performed. Finally, we verify the results by Monte-Carlo simulations of asymptotically optimal estimation algorithms.

Index Terms—1-bit ADC, Cramér-Rao bound, channel estimation, hard-limiting loss, intersymbol interference, nuisance parameter, quantization threshold, wireless communication

I. INTRODUCTION

THE design of signal processing systems is governed by two conflicting objectives. On the one hand, a system architecture which allows to obtain high operational performance and small latency, is desired. On the other hand, the processing device should exhibit low complexity, in particular with respect to its power consumption, production cost, and circuit size. In connection with the latter aspect, it has been identified that analog-to-digital (A/D) conversion forms a bottleneck [1], [2]. In this processing step, continuous waveforms

(analog signal domain), acquired at the receive sensors, are transformed into a representation which is discrete in time and amplitude (digital signal domain). The resulting output data can then be processed by sophisticated algorithms which are executed on dedicated hardware or by a general-purpose computer chip. As the complexity of the A/D conversion grows exponentially $\mathcal{O}(2^b)$ with the number of bits b which are used for the representation of the amplitude information, the A/D resolution restricts the receive bandwidth and significantly affects the overall energy consumption. Thus, although the majority of the signal processing literature focuses on data models with high amplitude resolution, an interesting system design option is to switch to sensors with coarse A/D resolution.

A. Low-Complexity 1-bit A/D Conversion

A radical approach is to use a single comparator, which forwards only the sign and discards all the information about the analog signal amplitude. This results in a cheap, small, and fast A/D converter (ADC) device with low energy consumption. Additionally, an automatic gain control (AGC) circuit [3] is not required for an ADC with single-bit output resolution. Due to these attractive properties, a vivid discussion on 1-bit quantization has emerged in the field of modern signal processing [4]–[10], while [11]–[13] are considered to be classical references for this topic. Furthermore, the problem of communication over noisy channels with 1-bit quantizer is considered in various recent works [14]–[18].

Despite of its low complexity, 1-bit A/D conversion introduces a nonlinearity into the system model, which is associated with a substantial performance loss. When the system operates in the low signal-to-noise ratio (SNR) regime, the loss is moderate with $2/\pi$ or −1.96 dB [12]. Further, the simplicity of the radio front-end allows to exploit other design options which are crucial for system performance. For example faster sampling rates [21]–[26] or a higher number of receive sensors [27], [28] allow to reduce the hard-limiting loss. Alternatively, the analog pre-filter [29] or the in-phase quadrature demodulator [30] can be adjusted in order to diminish the nonlinear processing loss of coarse resolution ADCs. Taking into account side-information about the temporal evolution of the channel parameters is also an effective approach in order to obtain high accuracy with 1-bit A/D conversion [31].

Another line of work, deals with the optimization of the 1-bit ADC by modification of the quantization level. In [32] it is shown that for pilot-based channel estimation a deterministic time-varying hard-limiting threshold yields a higher Fisher information than a random offset and therefore enables to

This work was supported by the German Academic Exchange Service (DAAD) with funds from the German Federal Ministry of Education and Research (BMBF) and the People Program (Marie Curie Actions) of the European Union's Seventh Framework Program (FP7) under REA grant agreement 605728 (P.R.I.M.E. - Postdoctoral Researchers International Mobility Experience). This work was also supported by the Israel Science Foundation (Grant 1160/15) and by the Yaakov ben Yitzhak Hacohen scholarship.

M. S. Stein is with the Mathematics Department (DWIS), Vrije Universiteit Brussel, Belgium (e-mail: manuel.stein@vub.ac.be). J. A. Nossek is with the Department of Teleinformatics Engineering, Universidade Federal do Ceará, Brasil, and also with the Department of Electrical and Computer Engineering, Technische Universität München, Germany (e-mail: josef.a.nossek@tum.de). S. Bar and J. Tabrikian are with the Department of Electrical and Computer Engineering, Ben-Gurion University of the Negev, Beer-Sheva, Israel (e-mail: shahba@post.bgu.ac.il, joseph@bgu.ac.il)

minimize the estimation error. The discussion in [33] aims at higher communication rates and studies maximization of Shannon information with asymmetric 1-bit quantization at the receiver. In contrast, the works [34]–[36] consider dithering, i.e., controlled randomization of the quantization level.

B. Motivation and Contribution

In practice, change of the quantization level during runtime requires to feedback analog control information to an offset voltage source. As the control signal has to be determined in the digital domain, a digital-to-analog converter (DAC) with high output resolution is required for the accurate adjustment of the quantization level. Since the complexity of DACs grows exponentially with the number of input bits, such an approach stands in contradiction to the goal of minimizing the radio front-end complexity by 1-bit A/D technology. Therefore for low-cost receivers the design of the 1-bit A/D conversion will be such that the offset is close to a predetermined constant value. Hardware imperfections, variations in the production process, and external effects, as discussed in [37], lead to the situation that the quantization offset is in general unknown. Therefore, calibration or a method which determines and compensates the offset during runtime is required.

In this paper, the problem of channel parameter estimation, subject to measurements attained with a 1-bit ADC under an unknown quantization threshold is studied. In order to provide a thorough discussion on the considered problem, we take two different modeling perspectives. First, with the mindset of frequentists [38]–[40], we assume that the parameters of interest and the quantization threshold are deterministic unknown variables. Then, we consider a hybrid model [41]–[45], where the channel parameters are random and distributed according to a known probability distribution function, while the quantization offset is modeled as a deterministic unknown nuisance parameter. The hybrid approach is motivated by the fact that prior information about the channel is available at the receiver in various cases. This information can be used to improve the estimation accuracy.

For both situations, we review asymptotically optimal estimation algorithms and study the achievable performance by analytic bounds or asymptotic expressions. In particular, we investigate the performance gaps between an ideal receiver with infinite ADC resolution, an asymmetric 1-bit ADC with known threshold, and an asymmetric 1-bit ADC with unknown threshold. In the low SNR regime we establish the result that missing offset knowledge does not degrade the estimation accuracy. For the problem of a wireless propagation channel with inter-symbol interference (ISI), we verify the results by Monte-Carlo simulations. This shows that the theoretic analysis accurately captures the performance trends in practical signal processing applications with 1-bit ADC and unknown quantization offset. The presented results are an extension of our conference contribution [46], which was confined to an observation model with a scalar channel parameter.

C. Outline

This paper is organized as follows. In Section II we define the general receive system models without and with 1-bit

A/D conversion. Section III discusses a deterministic and a hybrid modeling framework for the channel estimation task, outlines the asymptotically optimal estimation procedures and investigates their performance by analytic expressions. The estimation accuracy for operation in the low SNR regime is studied in Section IV, whereas in Section V we demonstrate the results for the specific application of wireless channel estimation with intersymbol interference. Additionally to the theoretic discussion, we validate our findings by Monte-Carlo simulations of practical signal processing algorithms. The final conclusions appear in Section VI.

II. SYSTEM MODEL

We consider two different system models. The first receive system features an ADC with b -bits output resolution, where b is sufficiently high such that the effect of amplitude quantization can be neglected. For simplicity, in the following we will refer to this setup as an ideal receiver with ∞ -bit ADC. The second system is a low-complexity receiver with 1-bit ADC resolution, where after the A/D conversion only binary information about the analog receive signal amplitude is available for further digital signal processing.

The receive signal of the ∞ -bit system at time instant n with $n = 1, \dots, N$ is modeled by the random variable $y_n \in \mathbb{R}$,

$$y_n \sim p_{y_n}(y_n|\boldsymbol{\theta}), \quad (1)$$

following a Gaussian conditional probability density function

$$p_{y_n}(y_n|\boldsymbol{\theta}) = (2\pi)^{-\frac{1}{2}} \exp\left(-\frac{1}{2}(y_n - s_n(\boldsymbol{\theta}))^2\right), \quad (2)$$

where $s_n(\boldsymbol{\theta}) \in \mathbb{R}$ is a pilot sequence of deterministic structure. The signal $s_n(\boldsymbol{\theta})$ is modulated by the channel parameters, summarized in the vector $\boldsymbol{\theta} \in \boldsymbol{\Theta} \subset \mathbb{R}^K$. Since one can always normalize the receive signal by its standard deviation, without loss of generality, the variance is assumed to be 1. Note the data model (1) can be extended to complex-valued receiver models by considering two independent real-valued random variables. As this has no impact onto the presented results, for the sake of simplicity, we focus on the real-valued case.

The receiver with 1-bit AD can be modeled

$$z_n = \text{sign}(y_n - \alpha), \quad (3)$$

where $\text{sign}(x)$ is the signum function defined as

$$\text{sign}(x) \triangleq \begin{cases} +1 & \text{if } x \geq 0 \\ -1 & \text{if } x < 0 \end{cases}, \quad (4)$$

$\alpha \in \mathbb{R}$ forms an unknown deterministic quantization threshold and $\triangleq$ denotes equality by definition.

With respect to the quantization model (3), it should be emphasized that we refer to an A/D conversion without feedback loop. This distinguishes the topic of low-complexity 1-bit ADCs from the sigma-delta modulation approach, in which a single comparator with feedback is operated in a highly oversampled mode in order to perform the A/D conversion [19], [20].

The quantized observation model (3) is characterized by a binary random variable $z_n \in \mathbb{B} \triangleq \{-1, 1\}$,

$$z_n \sim p_{z_n}(z_n|\psi), \quad (5)$$

following the conditional probability mass function

$$p_{z_n}(z_n|\psi) = Q(z_n(\alpha - s_n(\theta))), \quad (6)$$

where

$$Q(x) \triangleq \frac{1}{\sqrt{2\pi}} \int_x^\infty \exp\left(-\frac{u^2}{2}\right) du \quad (7)$$

is the Q-function. The probability mass function (6) is parametrized by the unknown vector parameter

$$\psi \triangleq [\theta^T \quad \alpha]^T \in \Psi \triangleq \Theta \times \mathbb{R}, \quad (8)$$

of which θ serves as the vector parameter of interest, while the offset α forms a nuisance parameter. Note that for compactness we do not distinguish between probability mass (5) and probability density functions (1). The respective case is always clear from the context.

The signal processing task of the receivers is to calculate the estimates $\hat{\theta}_y(\mathbf{y})$ and $\hat{\theta}_z(\mathbf{z})$ by using the N receive samples

$$\mathbf{y} = [y_1 \quad y_2 \quad \dots \quad y_N]^T, \quad (9)$$

or

$$\mathbf{z} = [z_1 \quad z_2 \quad \dots \quad z_N]^T \quad (10)$$

and the available information on the models (2) and (6).

III. THEORY - PERFORMANCE ANALYSIS

In order to characterize the performance gap between both systems, we discuss two different settings. For each of them we review the optimum estimation algorithm for the asymptotic regime and establish the achievable estimation performances by analytical error bounds or asymptotic error expressions.

A. Deterministic Modeling Approach

First, we study the case where the channel parameters θ and the threshold α are both deterministic but unknown.

1) *Estimation Procedure:* In this situation, the asymptotically optimum unbiased estimator with both receivers is the maximum-likelihood estimator (MLE) [47], given by

$$\begin{aligned} \hat{\theta}_y(\mathbf{y}) &\triangleq \arg \max_{\theta \in \Theta} p_y(\mathbf{y}|\theta) \\ &= \arg \max_{\theta \in \Theta} \sum_{n=1}^N \ln p_{y_n}(y_n|\theta) \end{aligned} \quad (11)$$

for the unquantized case and

$$\begin{aligned} \begin{bmatrix} \hat{\theta}_z^T(z) & \hat{\alpha}(z) \end{bmatrix}^T &\triangleq \arg \max_{\psi \in \Psi} p_z(\mathbf{z}|\theta, \alpha) \\ &= \arg \max_{\psi \in \Psi} \sum_{n=1}^N \ln p_{z_n}(z_n|\theta, \alpha) \end{aligned} \quad (12)$$

for the low-complexity 1-bit ADC receiver. Note that for the 1-bit system, the estimation of the channel parameters θ and the hard-limiting offset α has to be performed jointly. The

errors of the estimators $\hat{\theta}_y(\mathbf{y})$ and $\hat{\theta}_z(\mathbf{z})$ are evaluated under the mean squared error (MSE) criterion, such that

$$\text{MSE}_y(\theta) \triangleq \mathbb{E}_{\mathbf{y}|\theta} \left[(\hat{\theta}_y(\mathbf{y}) - \theta)(\hat{\theta}_y(\mathbf{y}) - \theta)^T \right], \quad (13)$$

$$\text{MSE}_z(\psi) \triangleq \mathbb{E}_{\mathbf{z}|\psi} \left[(\hat{\theta}_z(\mathbf{z}) - \theta)(\hat{\theta}_z(\mathbf{z}) - \theta)^T \right]. \quad (14)$$

Note that for the 1-bit receiver, the MSE in (14) is also a function of the offset α .

Under some mild regularity conditions (see [50]–[52]), in the asymptotic regime, the MSE of the ∞ -bit receiver in (13) implementing the MLE, is given by the Cramér-Rao lower bound (CRLB) [48], [49]

$$\text{MSE}_y(\theta) \stackrel{a}{=} \mathbf{F}^{-1}(\theta), \quad (15)$$

where, under the notational convention

$$\left[\frac{\partial \mathbf{g}(\mathbf{x})}{\partial \mathbf{x}} \right]_{ij} \triangleq \frac{\partial g_i(\mathbf{x})}{\partial x_j}, \quad (16)$$

the Fisher information matrix (FIM) [47] is defined as

$$\mathbf{F}(\theta) \triangleq \mathbb{E}_{\mathbf{y}|\theta} \left[\left(\frac{\partial \ln p_y(\mathbf{y}|\theta)}{\partial \theta} \right)^T \frac{\partial \ln p_y(\mathbf{y}|\theta)}{\partial \theta} \right] \quad (17)$$

and $\stackrel{a}{=}$ is used to denote asymptotic equality, i.e., equality after taking the number of samples N to infinity. Note that due to the statistical independence of the samples in (2), we have

$$\mathbf{F}(\theta) = \sum_{n=1}^N \mathbf{F}_n(\theta), \quad (18)$$

where

$$\begin{aligned} \mathbf{F}_n(\theta) &\triangleq \mathbb{E}_{y_n|\theta} \left[\left(\frac{\partial \ln p_{y_n}(y_n|\theta)}{\partial \theta} \right)^T \frac{\partial \ln p_{y_n}(y_n|\theta)}{\partial \theta} \right] \\ &= \left(\frac{\partial s_n(\theta)}{\partial \theta} \right)^T \frac{\partial s_n(\theta)}{\partial \theta} \\ &= \mathbf{f}_n^T(\theta) \mathbf{f}_n(\theta) \end{aligned} \quad (19)$$

with

$$\mathbf{f}_n(\theta) \triangleq \left(\frac{\partial s_n(\theta)}{\partial \theta} \right)^T. \quad (20)$$

For the 1-bit receiver (6), the FIM exhibits a block structure

$$\mathbf{J}(\psi) = \begin{bmatrix} \mathbf{J}_{\theta\theta}(\psi) & \mathbf{J}_{\theta\alpha}(\psi) \\ \mathbf{J}_{\alpha\theta}(\psi) & \mathbf{J}_{\alpha\alpha}(\psi) \end{bmatrix}, \quad (21)$$

such that the asymptotic MSE of the MLE estimator $\hat{\theta}_z(\mathbf{z})$ is equivalent to the CRLB

$$\text{MSE}_z(\psi) \stackrel{a}{=} \left(\mathbf{J}_{\theta\theta}(\psi) - \frac{\mathbf{J}_{\theta\alpha}(\psi) \mathbf{J}_{\alpha\theta}(\psi)}{\mathbf{J}_{\alpha\alpha}(\psi)} \right)^{-1}, \quad (22)$$

where the expressions required in (21) are given by

$$\mathbf{J}_{\theta\theta}(\psi) \triangleq \mathbb{E}_{\mathbf{z}|\psi} \left[\left(\frac{\partial \ln p_z(\mathbf{z}|\psi)}{\partial \theta} \right)^T \frac{\partial \ln p_z(\mathbf{z}|\psi)}{\partial \theta} \right], \quad (23)$$

$$\mathbf{J}_{\theta\alpha}(\psi) \triangleq \mathbb{E}_{\mathbf{z}|\psi} \left[\left(\frac{\partial \ln p_z(\mathbf{z}|\psi)}{\partial \theta} \right)^T \frac{\partial \ln p_z(\mathbf{z}|\psi)}{\partial \alpha} \right], \quad (24)$$

and

$$J_{\alpha\alpha}(\psi) \triangleq \mathbb{E}_{\mathbf{z}|\psi} \left[\left(\frac{\partial \ln p_{\mathbf{z}}(\mathbf{z}|\psi)}{\partial \alpha} \right)^2 \right]. \quad (25)$$

Note that we use the letter $\mathbf{J}$ for the FIMs associated with the quantized receiver (3) in order to clearly distinguish from the FIMs $\mathbf{F}$ associated with the ideal receiver (1).

Using (6) and the derivative $\frac{\partial Q(x)}{\partial x} = -\frac{1}{\sqrt{2\pi}} \exp\left(-\frac{x^2}{2}\right)$ of the Q-function from (7), we obtain

$$\frac{\partial \ln p_{z_n}(z_n|\psi)}{\partial \theta} = \frac{z_n \exp\left(-\frac{(\alpha - s_n(\theta))^2}{2}\right)}{\sqrt{2\pi} Q(z_n(\alpha - s_n(\theta)))} \frac{\partial s_n(\theta)}{\partial \theta}. \quad (26)$$

Using (6) and (26), with

$$\phi_n(\psi) \triangleq \frac{\exp\left(-(\alpha - s_n(\theta))^2\right)}{2\pi(Q(\alpha - s_n(\theta)) - Q^2(\alpha - s_n(\theta)))}, \quad (27)$$

we derive

$$\begin{aligned} \mathbb{E}_{z_n|\psi} \left[\left(\frac{\partial \ln p_{z_n}(z_n|\psi)}{\partial \theta} \right)^T \frac{\partial \ln p_{z_n}(z_n|\psi)}{\partial \theta} \right] &= \\ &= \phi_n(\psi) \left(\frac{\partial s_n(\theta)}{\partial \theta} \right)^T \frac{\partial s_n(\theta)}{\partial \theta}, \end{aligned} \quad (28)$$

where the step-by-step calculation is given in Appendix A.

Therefore, we can write the first FIM block from (23)

$$\begin{aligned} \mathbf{J}_{\theta\theta}(\psi) &= \sum_{n=1}^N \mathbb{E}_{z_n|\psi} \left[\left(\frac{\partial \ln p_{z_n}(z_n|\psi)}{\partial \theta} \right)^T \frac{\partial \ln p_{z_n}(z_n|\psi)}{\partial \theta} \right] \\ &= \sum_{n=1}^N \phi_n(\psi) \left(\frac{\partial s_n(\theta)}{\partial \theta} \right)^T \frac{\partial s_n(\theta)}{\partial \theta} \\ &= \sum_{n=1}^N \phi_n(\psi) \mathbf{F}_n(\theta), \end{aligned} \quad (29)$$

where the first equality stems from the FIM property (18) with independent samples. Accordingly, with

$$\frac{\partial \ln p_{z_n}(z_n|\psi)}{\partial \alpha} = -\frac{z_n \exp\left(-\frac{z_n(\alpha - s_n(\theta))^2}{2}\right)}{\sqrt{2\pi} Q(z_n(\alpha - s_n(\theta)))}, \quad (30)$$

we write (24) and (25) as

$$\begin{aligned} \mathbf{J}_{\theta\alpha}(\psi) &= -\sum_{n=1}^N \phi_n(\psi) \left(\frac{\partial s_n(\theta)}{\partial \theta} \right)^T \\ &= -\sum_{n=1}^N \phi_n(\psi) \mathbf{f}_n(\theta), \end{aligned} \quad (31)$$

$$J_{\alpha\alpha}(\psi) = \sum_{n=1}^N \phi_n(\psi). \quad (32)$$

In the case where the threshold α is known to the receiver, the asymptotic MSE of the MLE

$$\begin{aligned} \hat{\theta}_{\mathbf{z}}^* &\triangleq \arg \max_{\theta \in \Theta} p_{\mathbf{z}}(\mathbf{z}|\theta, \alpha) \\ &= \arg \max_{\theta \in \Theta} \sum_{n=1}^N \ln p_{z_n}(z_n|\theta, \alpha) \end{aligned} \quad (33)$$

is equivalent to

$$\text{MSE}_{\mathbf{z}}^*(\psi) \stackrel{a}{=} \mathbf{J}_{\theta\theta}^{-1}(\psi). \quad (34)$$

2) *Performance Measures:* For the comparison between the performance of the ideal (11) and the quantized receivers (12) and (33), we define the average ratios between the MSEs

$$\chi(\psi) \triangleq \frac{1}{K} \sum_{k=1}^K \frac{[\text{MSE}_{\mathbf{y}}(\theta)]_{kk}}{[\text{MSE}_{\mathbf{z}}(\psi)]_{kk}}, \quad (35)$$

$$\chi^*(\psi) \triangleq \frac{1}{K} \sum_{k=1}^K \frac{[\text{MSE}_{\mathbf{y}}(\theta)]_{kk}}{[\text{MSE}_{\mathbf{z}}^*(\psi)]_{kk}}. \quad (36)$$

The measures (35) and (36) can be interpreted as the performance loss (averaged over the K parameters) which is introduced by hard-limiting the signal $\mathbf{y}$. The explicit performance loss introduced in the quantized case by having to estimate the unknown threshold in (12) can be characterized by

$$\Upsilon(\psi) \triangleq \frac{1}{K} \sum_{k=1}^K \frac{[\text{MSE}_{\mathbf{z}}^*(\psi)]_{kk}}{[\text{MSE}_{\mathbf{z}}(\psi)]_{kk}}. \quad (37)$$

B. Hybrid Modeling Approach

The second approach we consider is the case where the parameter $\theta \sim p(\theta)$ is modeled as a random vector and the threshold α is an unknown deterministic nuisance parameter.

1) *Estimation Procedure:* In this scenario, the asymptotically optimum estimator with the ideal receiver (1) is the *maximum a-posteriori probability* (MAP) estimator [56]

$$\begin{aligned} \hat{\theta}_{\mathbf{y}}(\mathbf{y}) &\triangleq \arg \max_{\theta \in \Theta} p_{\mathbf{y},\theta}(\mathbf{y}, \theta) \\ &= \arg \max_{\theta \in \Theta} (\ln p_{\mathbf{y}}(\mathbf{y}|\theta) + \ln p_{\theta}(\theta)), \end{aligned} \quad (38)$$

where the last equality stems from the Bayes' law. For the 1-bit receiver (3), the asymptotically optimum estimator [53] is the joint MAP-MLE (JMAP-MLE) [54], given by

$$\begin{aligned} [\hat{\theta}_{\mathbf{z}}(\mathbf{z}) \quad \hat{\alpha}(\mathbf{z})]^T &\triangleq \arg \max_{\psi \in \Psi} p_{\mathbf{z}}(\mathbf{z}|\psi, \alpha) \\ &= \arg \max_{\psi \in \Psi} (\ln p_{\mathbf{z}}(\mathbf{z}|\theta, \alpha) + \ln p_{\theta}(\theta)), \end{aligned} \quad (39)$$

where the last equality stems from the Bayes' law and the assumption that the prior probability density function of the random parameters θ is independent of the threshold α . In the hybrid framework, the errors of the estimators $\hat{\theta}_{\mathbf{y}}(\mathbf{y})$ and $\hat{\theta}_{\mathbf{z}}(\mathbf{z})$ are defined as

$$\text{MSE}_{\mathbf{y}} \triangleq \mathbb{E}_{\mathbf{y},\theta} \left[(\hat{\theta}_{\mathbf{y}}(\mathbf{y}) - \theta) (\hat{\theta}_{\mathbf{y}}(\mathbf{y}) - \theta)^T \right], \quad (40)$$

$$\text{MSE}_{\mathbf{z}}(\alpha) \triangleq \mathbb{E}_{\mathbf{z},\theta|\alpha} \left[(\hat{\theta}_{\mathbf{z}}(\mathbf{z}) - \theta) (\hat{\theta}_{\mathbf{z}}(\mathbf{z}) - \theta)^T \right]. \quad (41)$$

For the ideal receiver, the asymptotic performance of the MAP estimator is obtained by using the expected value of the CRLB in (15), known as the expected CRLB (ECRLB) [55] [56, p. 6]. Correspondingly, the MSE of the optimal infinite-resolution receiver (40) asymptotically converges to

$$\text{MSE}_{\mathbf{y}} \stackrel{a}{=} \mathbb{E}_{\theta} [\mathbf{F}^{-1}(\theta)]. \quad (42)$$

Note that traditionally, the MSE of Bayesian parameter estimators is lower bounded by the Bayesian CRLB (BCRLB) [56, p. 5], given by

$$\text{MSE}_{\mathbf{y}} \succeq (\mathbb{E}_{\theta} [\mathbf{F}(\theta)] + \mathbf{J}_P)^{-1}, \quad (43)$$

where $\mathbf{J}_P$ is the prior FIM, given by

$$\mathbf{J}_P \triangleq \mathbb{E}_\theta \left[\left(\frac{\partial \ln p_\theta(\boldsymbol{\theta})}{\partial \boldsymbol{\theta}} \right)^T \frac{\partial \ln p_\theta(\boldsymbol{\theta})}{\partial \boldsymbol{\theta}} \right]. \quad (44)$$

However, this lower bound is only attainable in special cases, while the ECRLB is in general asymptotically attainable [56, p. 6]. For the performance analysis of the 1-bit receive model (3), one can suggest the utilization of the hybrid CRLB (HCRLB), given by [41], [42], [44]

$$\text{MSE}_z(\alpha) \geq \left(\mathbb{E}_\theta [\mathbf{J}_{\theta\theta}(\boldsymbol{\psi})] - \frac{\mathbb{E}_\theta [\mathbf{J}_{\theta\alpha}(\boldsymbol{\psi})] \mathbb{E}_\theta [\mathbf{J}_{\alpha\theta}(\boldsymbol{\psi})]}{\mathbb{E}_\theta [\mathbf{J}_{\alpha\alpha}(\boldsymbol{\psi})]} + \mathbf{J}_P \right)^{-1}. \quad (45)$$

This bound is traditionally used to lower bound the MSE of unbiased parameter estimators in the hybrid setup. However, in contrast to the CRLB, this lower bound is only attainable in special cases, even asymptotically [53]. Thus, in order to characterize the asymptotic performance of the JMAP-MLE, the following theorem is given.

Theorem 1 (Expected HCRLB (EHCRLB)). Let us assume that as the number of measurements N increases, the JMAP-MLE coincides with the MLE, given by

$$[\hat{\boldsymbol{\theta}}_z(\mathbf{z}) \quad \hat{\alpha}(\mathbf{z})]^T = \arg \max_{\boldsymbol{\psi} \in \Psi} \ln p_z(\mathbf{z}|\boldsymbol{\psi}),$$

in the sense of convergence in probability [57] and that the sequence of MLEs as a function of the number of measurements is asymptotically uniformly integrable [58]. Then,

$$\text{MSE}_z(\alpha) \stackrel{a}{=} \mathbb{E}_\theta \left[\left(\mathbf{J}_{\theta\theta}(\boldsymbol{\psi}) - \frac{\mathbf{J}_{\theta\alpha}(\boldsymbol{\psi}) \mathbf{J}_{\alpha\theta}(\boldsymbol{\psi})}{\mathbf{J}_{\alpha\alpha}(\boldsymbol{\psi})} \right)^{-1} \right]. \quad (46)$$

Proof: see Appendix B. ■

Note that the r.h.s. of (46) represents the hybrid version of the ECRLB, denoted by EHCRLB. While it does not constitute a lower bound, the EHCRLB is asymptotically attainable by the JMAP-MLE. To the best of the authors' knowledge, no previous work in the literature has presented this performance analysis tool in the hybrid context. Again, due to Jensen's inequality [60, p. 83-84]

$$\begin{aligned} & \mathbb{E}_\theta \left[\left(\mathbf{J}_{\theta\theta}(\boldsymbol{\psi}) - \frac{\mathbf{J}_{\theta\alpha}(\boldsymbol{\psi}) \mathbf{J}_{\alpha\theta}(\boldsymbol{\psi})}{\mathbf{J}_{\alpha\alpha}(\boldsymbol{\psi})} \right)^{-1} \right] \geq \\ & \geq \left\{ \mathbb{E}_\theta \left[\left(\mathbf{J}_{\theta\theta}(\boldsymbol{\psi}) - \frac{\mathbf{J}_{\theta\alpha}(\boldsymbol{\psi}) \mathbf{J}_{\alpha\theta}(\boldsymbol{\psi})}{\mathbf{J}_{\alpha\alpha}(\boldsymbol{\psi})} \right) \right] \right\}^{-1} \\ & \geq \left\{ \mathbb{E}_\theta [\mathbf{J}_{\theta\theta}(\boldsymbol{\psi})] - \frac{\mathbb{E}_\theta [\mathbf{J}_{\theta\alpha}(\boldsymbol{\psi})] \mathbb{E}_\theta [\mathbf{J}_{\alpha\theta}(\boldsymbol{\psi})]}{\mathbb{E}_\theta [\mathbf{J}_{\alpha\alpha}(\boldsymbol{\psi})]} \right\}^{-1}, \quad (47) \end{aligned}$$

where the last inequality is obtained using the covariance inequality [61, p. 113], given by

$$\mathbb{E}_\theta [\mathbf{u}\mathbf{u}^T] \succeq \mathbb{E}_\theta [\mathbf{u}\mathbf{w}^T] \mathbb{E}_\theta^{-1} [\mathbf{w}\mathbf{w}^T] \mathbb{E}_\theta [\mathbf{w}\mathbf{u}^T], \quad (48)$$

for some random vectors $\mathbf{u}$ and $\mathbf{w}$, by setting $\mathbf{u} = \frac{\mathbf{J}_{\theta\alpha}(\boldsymbol{\psi})}{\sqrt{\mathbf{J}_{\alpha\alpha}(\boldsymbol{\psi})}}$ and $\mathbf{w} = \sqrt{\mathbf{J}_{\alpha\alpha}(\boldsymbol{\psi})}$. The r.h.s. of (47) can be identified as

the asymptotic version (when the prior information about $\boldsymbol{\theta}$ is negligible) of HCRLB in (45). That is, while the expression in (46) can in general be asymptotically achieved by the JMAP-MLE, the r.h.s. of (47) serves only as a lower bound and is only achieved under special conditions [53]. Thus, the EHCRLB and the HCRLB present relations similar to the aforementioned relations between the ECRLB and BCRLB.

In case that the quantization offset α is known to the receiver, we proceed by using the MAP estimator

$$\hat{\boldsymbol{\theta}}^*(\mathbf{z}) = \arg \max_{\boldsymbol{\theta} \in \Theta} \ln p_z(\mathbf{z}|\boldsymbol{\theta}, \alpha) \quad (49)$$

with asymptotic MSE

$$\text{MSE}_z^*(\alpha) \stackrel{a}{=} \mathbb{E}_\theta [\mathbf{J}_{\theta\theta}^{-1}(\boldsymbol{\psi})] \quad (50)$$

and the error bound

$$\text{MSE}_z^*(\alpha) \geq \left(\mathbb{E}_\theta [\mathbf{J}_{\theta\theta}(\boldsymbol{\psi})] + \mathbf{J}_P \right)^{-1}. \quad (51)$$

2) *Performance Measures:* Note that for the hybrid modeling approach the quantization loss measures

$$\chi(\alpha) \triangleq \frac{1}{K} \sum_{k=1}^K \frac{[\text{MSE}_y]_{kk}}{[\text{MSE}_z(\alpha)]_{kk}}, \quad (52)$$

$$\chi^*(\alpha) \triangleq \frac{1}{K} \sum_{k=1}^K \frac{[\text{MSE}_y]_{kk}}{[\text{MSE}_z^*(\alpha)]_{kk}}, \quad (53)$$

only depend on the quantization offset α . According to the deterministic modeling approach, we define the performance penalty introduced by the estimation of the unknown quantization offset as

$$\Upsilon(\alpha) \triangleq \frac{1}{K} \sum_{k=1}^K \frac{[\text{MSE}_z^*(\alpha)]_{kk}}{[\text{MSE}_z(\alpha)]_{kk}}. \quad (54)$$

IV. PERFORMANCE ANALYSIS FOR LOW SNR

In this section, the results of the deterministic and the hybrid approaches are discussed under the assumption that the channel estimation task takes place in the low SNR regime. Such an assumption is well-motivated in cases where the radio transmitter and receiver are far apart, like for example in a satellite communication link or when weak receive signals have to be processed as in radar applications. In order to define the low SNR regime in a consistent manner, we assume the existence of some (not necessarily unique) $\boldsymbol{\theta}_0 \in \Theta$ for which

$$s_n(\boldsymbol{\theta}_0) \rightarrow 0, \quad \forall n, \quad \text{when } \boldsymbol{\theta} \rightarrow \boldsymbol{\theta}_0. \quad (55)$$

A. Deterministic Approach

Since in the low SNR regime the pilot signal $s_n(\boldsymbol{\theta})$ tends to zero, we define

$$\begin{aligned} \phi_0(\alpha) & \triangleq \lim_{\boldsymbol{\theta} \rightarrow \boldsymbol{\theta}_0} \phi_n(\boldsymbol{\psi}) \\ & = \frac{\exp(-\alpha^2)}{2\pi(Q(\alpha) - Q^2(\alpha))}. \end{aligned} \quad (56)$$

Hence, with the functions $\mathbf{F}(\boldsymbol{\theta})$, $\mathbf{F}_n(\boldsymbol{\theta})$, $\mathbf{f}_n(\boldsymbol{\theta})$ defined in (17), (19), (20) and

$$\mathbf{f}(\boldsymbol{\theta}) \triangleq \sum_{n=1}^N \mathbf{f}_n(\boldsymbol{\theta}), \quad (57)$$

the FIM elements in (29), (31), and (32) associated with the quantized receiver, become

$$\begin{aligned} \lim_{\boldsymbol{\theta} \rightarrow \boldsymbol{\theta}_0} \mathbf{J}_{\boldsymbol{\theta}\boldsymbol{\theta}}(\boldsymbol{\psi}) &= \sum_{n=1}^N \phi_0(\alpha) \mathbf{F}_n(\boldsymbol{\theta}_0) \\ &= \phi_0(\alpha) \mathbf{F}(\boldsymbol{\theta}_0), \end{aligned} \quad (58)$$

$$\begin{aligned} \lim_{\boldsymbol{\theta} \rightarrow \boldsymbol{\theta}_0} \mathbf{J}_{\boldsymbol{\theta}\alpha}(\boldsymbol{\psi}) &= - \sum_{n=1}^N \phi_0(\alpha) \mathbf{f}_n(\boldsymbol{\theta}_0) \\ &= -\phi_0(\alpha) \mathbf{f}(\boldsymbol{\theta}_0), \end{aligned} \quad (59)$$

and

$$\lim_{\boldsymbol{\theta} \rightarrow \boldsymbol{\theta}_0} J_{\alpha\alpha}(\boldsymbol{\psi}) = N\phi_0(\alpha). \quad (60)$$

Substitution of (58)-(60) into (22), yields

$$\begin{aligned} \lim_{\boldsymbol{\theta} \rightarrow \boldsymbol{\theta}_0} \text{MSE}_{\mathbf{z}}(\boldsymbol{\psi}) &\stackrel{a}{=} \lim_{\boldsymbol{\theta} \rightarrow \boldsymbol{\theta}_0} \left(\mathbf{J}_{\boldsymbol{\theta}\boldsymbol{\theta}}(\boldsymbol{\psi}) - \frac{\mathbf{J}_{\boldsymbol{\theta}\alpha}(\boldsymbol{\psi}) \mathbf{J}_{\alpha\boldsymbol{\theta}}(\boldsymbol{\psi})}{J_{\alpha\alpha}(\boldsymbol{\psi})} \right)^{-1} \\ &= \frac{1}{\phi_0(\alpha)} \left(\mathbf{F}(\boldsymbol{\theta}_0) - \frac{1}{N} \mathbf{f}(\boldsymbol{\theta}_0) \mathbf{f}^T(\boldsymbol{\theta}_0) \right)^{-1}. \end{aligned} \quad (61)$$

From (18) and (57) it can be observed that the entries of $\mathbf{F}(\boldsymbol{\theta})$ and $\mathbf{f}(\boldsymbol{\theta})$ grow linearly with the number of samples N . The matrix entries of

$$\mathbf{f}(\boldsymbol{\theta}) \mathbf{f}^T(\boldsymbol{\theta}) = \sum_{n=1}^N \mathbf{f}_n(\boldsymbol{\theta}) \mathbf{f}_n^T(\boldsymbol{\theta}) + \sum_{\substack{n=1, m=1 \\ n \neq m}}^{N, N} \mathbf{f}_n(\boldsymbol{\theta}) \mathbf{f}_m^T(\boldsymbol{\theta}) \quad (62)$$

grow linearly if the entries of the second term exhibit a growth rate of linear order, i.e.,

$$\sum_{\substack{n=1, m=1 \\ n \neq m}}^{N, N} \mathbf{f}_n(\boldsymbol{\theta}) \mathbf{f}_m^T(\boldsymbol{\theta}) \sim \mathcal{O}(N). \quad (63)$$

For all cases where (63) is satisfied through the channel model or the pilot signal design, the asymptotic 1-bit MSE in the low SNR regime (61) can be simplified to

$$\lim_{\boldsymbol{\theta} \rightarrow \boldsymbol{\theta}_0} \text{MSE}_{\mathbf{z}}(\boldsymbol{\psi}) \stackrel{a}{=} \frac{1}{\phi_0(\alpha)} \mathbf{F}^{-1}(\boldsymbol{\theta}_0).$$

With

$$\lim_{\boldsymbol{\theta} \rightarrow \boldsymbol{\theta}_0} \text{MSE}_{\mathbf{y}}(\boldsymbol{\theta}) \stackrel{a}{=} \mathbf{F}^{-1}(\boldsymbol{\theta}_0), \quad (64)$$

the quantization loss (35) then tends towards

$$\begin{aligned} \lim_{\boldsymbol{\theta} \rightarrow \boldsymbol{\theta}_0} \chi(\boldsymbol{\psi}) &= \frac{1}{K} \sum_{k=1}^K \frac{[\lim_{\boldsymbol{\theta} \rightarrow \boldsymbol{\theta}_0} \text{MSE}_{\mathbf{y}}(\boldsymbol{\theta})]_{kk}}{[\lim_{\boldsymbol{\theta} \rightarrow \boldsymbol{\theta}_0} \text{MSE}_{\mathbf{z}}(\boldsymbol{\psi})]_{kk}} \\ &\stackrel{a}{=} \phi_0(\alpha). \end{aligned} \quad (65)$$

Note, that for the symmetric case, i.e., $\alpha = 0$, with $Q(0) = \frac{1}{2}$ we obtain the classical coarse quantization result [12]

$$\phi_0(0) = \frac{1}{2\pi(Q(0) - Q^2(0))} = \frac{2}{\pi}. \quad (66)$$

For the quantized receiver with known offset (33), we have

$$\lim_{\boldsymbol{\theta} \rightarrow \boldsymbol{\theta}_0} \text{MSE}_{\mathbf{z}}^*(\boldsymbol{\psi}) \stackrel{a}{=} \frac{1}{\phi_0(\alpha)} \mathbf{F}^{-1}(\boldsymbol{\theta}_0) \quad (67)$$

and

$$\begin{aligned} \lim_{\boldsymbol{\theta} \rightarrow \boldsymbol{\theta}_0} \chi^*(\boldsymbol{\psi}) &= \frac{1}{K} \sum_{k=1}^K \frac{[\lim_{\boldsymbol{\theta} \rightarrow \boldsymbol{\theta}_0} \text{MSE}_{\mathbf{y}}(\boldsymbol{\theta})]_{kk}}{[\lim_{\boldsymbol{\theta} \rightarrow \boldsymbol{\theta}_0} \text{MSE}_{\mathbf{z}}^*(\boldsymbol{\psi})]_{kk}} \\ &\stackrel{a}{=} \phi_0(\alpha), \end{aligned} \quad (68)$$

such that for all cases where (63) is satisfied, the loss (37) introduced by the estimation of the unknown offset in (12) vanishes

$$\lim_{\boldsymbol{\theta} \rightarrow \boldsymbol{\theta}_0} \Upsilon(\boldsymbol{\psi}) \stackrel{a}{=} 1. \quad (69)$$

B. Hybrid Approach

In order to adapt the low SNR regime definition (55) to the hybrid scenario, we interpret the required limit procedure in the following manner. It is assumed that the prior $p_{\boldsymbol{\theta}}(\boldsymbol{\theta})$ can be controlled by a set of parameters $\boldsymbol{\gamma} \in \boldsymbol{\Gamma}$, such that $p_{\boldsymbol{\theta}}(\boldsymbol{\theta}; \boldsymbol{\gamma})$ stands for the parameterized prior. Furthermore,

$$\exists \boldsymbol{\gamma}_0 : \lim_{\boldsymbol{\gamma} \rightarrow \boldsymbol{\gamma}_0} p_{\boldsymbol{\theta}}(s_n(\boldsymbol{\theta}) \rightarrow 0; \boldsymbol{\gamma}) = 1, \quad \forall n, \boldsymbol{\theta} \in \boldsymbol{\Theta}(\boldsymbol{\gamma}_0), \quad (70)$$

where

$$\boldsymbol{\Theta}(\boldsymbol{\gamma}_0) = \{\boldsymbol{\theta} \mid \lim_{\boldsymbol{\gamma} \rightarrow \boldsymbol{\gamma}_0} p(\boldsymbol{\theta}; \boldsymbol{\gamma}) \neq 0\}, \quad (71)$$

is the significant support of the random parameter $\boldsymbol{\theta}$ at $\boldsymbol{\gamma}_0$. By taking the limit of both sides of (46) as $\boldsymbol{\gamma}$ tends to $\boldsymbol{\gamma}_0$ yields

$$\begin{aligned} \lim_{\boldsymbol{\gamma} \rightarrow \boldsymbol{\gamma}_0} \text{MSE}_{\mathbf{z}}(\alpha) &\stackrel{a}{=} \\ &\stackrel{a}{=} \lim_{\boldsymbol{\gamma} \rightarrow \boldsymbol{\gamma}_0} \mathbb{E}_{\boldsymbol{\theta}; \boldsymbol{\gamma}} \left[\left(\mathbf{J}_{\boldsymbol{\theta}\boldsymbol{\theta}}(\boldsymbol{\psi}) - \frac{\mathbf{J}_{\boldsymbol{\theta}\alpha}(\boldsymbol{\psi}) \mathbf{J}_{\alpha\boldsymbol{\theta}}(\boldsymbol{\psi})}{J_{\alpha\alpha}(\boldsymbol{\psi})} \right)^{-1} \right]. \end{aligned} \quad (72)$$

Hence, (61), (67), and (70) imply that the expression inside the expectation term can be interchanged, such that

$$\begin{aligned} \lim_{\boldsymbol{\gamma} \rightarrow \boldsymbol{\gamma}_0} \text{MSE}_{\mathbf{z}}(\alpha) &\stackrel{a}{=} \lim_{\boldsymbol{\gamma} \rightarrow \boldsymbol{\gamma}_0} \text{MSE}_{\mathbf{z}}^*(\alpha) \\ &= \frac{1}{\phi_0(\alpha)} \mathbb{E}_{\boldsymbol{\theta}; \boldsymbol{\gamma}_0} [\mathbf{F}^{-1}(\boldsymbol{\theta})] \end{aligned} \quad (73)$$

for all cases where (63) holds, while (42) leads to

$$\lim_{\boldsymbol{\gamma} \rightarrow \boldsymbol{\gamma}_0} \text{MSE}_{\mathbf{y}} \stackrel{a}{=} \mathbb{E}_{\boldsymbol{\theta}; \boldsymbol{\gamma}_0} [\mathbf{F}^{-1}(\boldsymbol{\theta})]. \quad (74)$$

Therefore, under the restriction in (63), for the hybrid quantization losses (52) and (53),

$$\lim_{\boldsymbol{\gamma} \rightarrow \boldsymbol{\gamma}_0} \chi(\alpha) \stackrel{a}{=} \lim_{\boldsymbol{\gamma} \rightarrow \boldsymbol{\gamma}_0} \chi^*(\alpha) = \phi_0(\alpha), \quad (75)$$

such that the accuracy loss due to offset estimation in (54) vanishes when operating in the low SNR regime, i.e.,

$$\lim_{\boldsymbol{\gamma} \rightarrow \boldsymbol{\gamma}_0} \Upsilon(\alpha) \stackrel{a}{=} 1. \quad (76)$$

V. APPLICATION - WIRELESS CHANNEL ESTIMATION

Using the generic expressions from the previous sections, we analyze the performance gap between the ideal receiver (1) with high ADC resolution and the low-complexity receiver (3) with 1-bit ADC for a wireless channel with inter-symbol interference (ISI). Such a channel estimation problem occurs in the application of mobile communication, where channel characteristics like multi-path propagation or nonlinear frequency response of the time-varying wireless propagation medium have to be measured in a recurrent manner.

A. Multi-tap Channel Estimation

The signal model of the ISI channel is

$$y_n = \sum_{k=1}^K h_k x_{n-k+1} + \eta_n, \quad (77)$$

where $h_k \in \mathbb{R}$ is the receive strength of the k -th channel tap and $x_n \in \{-1, 1\}$ a binary pilot signal (BPSK) of known structure, even length N and with symmetric symbol assignment, i.e., $\sum_{n=1}^N x_n = 0$. Further, we define the vector $\mathbf{x}_n \in \{-1, 1\}^K$ with column entries

$$[\mathbf{x}_n]_i = x_{n-i+1}, \quad i = 1, \dots, K \quad (78)$$

and the matrix $\mathbf{X}_n \in \{-1, 1\}^{K \times K}$

$$\mathbf{X}_n = \mathbf{x}_n \mathbf{x}_n^T. \quad (79)$$

The ISI-channel estimation task is to determine the channel coefficients, summarized in the parameter vector

$$\boldsymbol{\theta} = [h_1 \ h_2 \ \dots \ h_K]^T, \quad (80)$$

from the receive signals

$$y_n = s_n(\boldsymbol{\theta}) + \eta_n = \mathbf{x}_n^T \boldsymbol{\theta} + \eta_n. \quad (81)$$

A wireless receiver with a 1-bit A/D conversion observes the quantized signal samples

$$z_n = \text{sign}(\mathbf{x}_n^T \boldsymbol{\theta} + \eta_n - \alpha). \quad (82)$$

Note that for the considered ISI scenario (81) one obtains $\mathbf{f}_n(\boldsymbol{\theta}) = \mathbf{x}_n$. Therefore, with a binary pilot signal following a symmetric symbol assignment it can be verified

$$\sum_{\substack{n=1, m=1 \\ n \neq m}}^{N, N} \mathbf{x}_n \mathbf{x}_m^T \sim \mathcal{O}(1), \quad (83)$$

such that (63) is fulfilled and the analytic low SNR results (65), (69), (75), and (76) hold for the ISI channel model (82).

1) *Performance Analysis - Deterministic Approach:* Under the deterministic framework the FIM (17) for the ideal wireless receive system (77) is given by

$$\mathbf{F}(\boldsymbol{\theta}) = \sum_{n=1}^N \mathbf{X}_n, \quad (84)$$

such that

$$\text{MSE}_{\mathbf{y}}(\boldsymbol{\theta}) \stackrel{a}{=} \left(\sum_{n=1}^N \mathbf{X}_n \right)^{-1}. \quad (85)$$

For the 1-bit quantized receiver (82), with (27) we obtain

$$\phi_n(\boldsymbol{\psi}) = \frac{\exp\left(-\left(\alpha - \sum_k h_k x_{n-k+1}\right)^2\right)}{2\pi\left(Q\left(\alpha - \sum_k h_k x_{n-k+1}\right) - Q^2\left(\alpha - \sum_k h_k x_{n-k+1}\right)\right)}, \quad (86)$$

such that the quantized FIMs (29), (31), and (32) are

$$\mathbf{J}_{\boldsymbol{\theta}\boldsymbol{\theta}}(\boldsymbol{\psi}) = \sum_{n=1}^N \phi_n(\boldsymbol{\psi}) \mathbf{X}_n, \quad (87)$$

$$\mathbf{J}_{\boldsymbol{\theta}\alpha}(\boldsymbol{\psi}) = - \sum_{n=1}^N \phi_n(\boldsymbol{\psi}) \mathbf{x}_n, \quad (88)$$

$$J_{\alpha\alpha}(\boldsymbol{\psi}) = \sum_{n=1}^N \phi_n(\boldsymbol{\psi}). \quad (89)$$

Under the low SNR assumption, with (56) we derive

$$\lim_{\boldsymbol{\theta} \rightarrow 0} \mathbf{J}_{\boldsymbol{\theta}\boldsymbol{\theta}}(\boldsymbol{\psi}) = \phi_0(\alpha) \sum_{n=1}^N \mathbf{X}_n, \quad (90)$$

$$\lim_{\boldsymbol{\theta} \rightarrow 0} \mathbf{J}_{\boldsymbol{\theta}\alpha}(\boldsymbol{\psi}) = -\phi_0(\alpha) \sum_{n=1}^N \mathbf{x}_n, \quad (91)$$

and

$$\lim_{\boldsymbol{\theta} \rightarrow 0} J_{\alpha\alpha}(\boldsymbol{\psi}) = N\phi_0(\alpha). \quad (92)$$

With (61) and (67), we obtain the asymptotic MSEs

$$\lim_{\boldsymbol{\theta} \rightarrow 0} \text{MSE}_{\mathbf{z}}(\boldsymbol{\psi}) \stackrel{a}{=} \frac{1}{\phi_0(\alpha)} \left(\sum_{n=1}^N \mathbf{X}_n \right)^{-1}, \quad (93)$$

and

$$\lim_{\boldsymbol{\theta} \rightarrow 0} \text{MSE}_{\mathbf{z}}^*(\boldsymbol{\psi}) \stackrel{a}{=} \frac{1}{\phi_0(\alpha)} \left(\sum_{n=1}^N \mathbf{X}_n \right)^{-1}, \quad (94)$$

in the low SNR regime. Therefore, like predicted in (65), the loss (37) introduced by the unknown offset vanishes, i.e.,

$$\lim_{\boldsymbol{\theta} \rightarrow 0} \chi(\boldsymbol{\psi}) = \lim_{\boldsymbol{\theta} \rightarrow 0} \chi^*(\boldsymbol{\psi}) = \phi_0(\alpha), \quad (95)$$

in accordance with (69).

2) *Results - Deterministic Approach:* For the simulations of the ISI channel estimation task, we assume

$$h_k^2 = \text{SNR}_k. \quad (96)$$

Considering a scenario with $K = 3$ channel taps and $N = 1024$ symbols, we set the signal strength of the interfering symbols to $\text{SNR}_2 = \text{SNR}_1 - 3$ dB, $\text{SNR}_3 = \text{SNR}_1 - 6$ dB and average the estimation error of $\hat{\boldsymbol{\theta}}_{\mathbf{y}}(\mathbf{y})$, $\hat{\boldsymbol{\theta}}_{\mathbf{z}}(\mathbf{z})$, and $\hat{\boldsymbol{\theta}}_{\mathbf{z}}^*(\mathbf{z})$ over 1000 noise realizations. The performance is evaluated by the root-normalized MSE (RNMSE)

$$\text{RNMSE}_{\mathbf{y}}(\boldsymbol{\theta}) = \sqrt{\frac{1}{K} \sum_{k=1}^K \frac{[\text{MSE}_{\mathbf{y}}(\boldsymbol{\theta})]_{kk}}{h_k^2}} \quad (97)$$

for the ideal receiver and

$$\text{RNMSE}_z(\psi) = \sqrt{\frac{1}{K} \sum_{k=1}^K \frac{[\text{MSE}_z(\psi)]_{kk}}{h_k^2}}, \quad (98)$$

$$\text{RNMSE}_z^*(\psi) = \sqrt{\frac{1}{K} \sum_{k=1}^K \frac{[\text{MSE}_z^*(\psi)]_{kk}}{h_k^2}} \quad (99)$$

for the two 1-bit receive systems. Figs. 1 and 2 illustrates the




Fig. 1: MSE - Deterministic ISI Channel ($\text{SNR}_1 = -21$ dB)

RNMSEs (97)-(99) for the low SNR regime ($\text{SNR}_1 = -21$ dB) and the medium SNR regime ($\text{SNR}_1 = -3$ dB), respectively. It can be observed that for both scenarios (Figs. 1 and




Fig. 2: MSE - Deterministic ISI Channel ($\text{SNR}_1 = -3$ dB)

2) the CRLBs accurately characterize the performance of the MLEs. In Fig. 3 we visualize the performance loss defined in (35) and (36) due to hard-limiting the receive signal (82). It can be observed that the loss is less pronounced in the low SNR setup while in general it increases with the quantization offset α . For the considered ISI scenario, the accuracy degradation due to the uncertainty in the unknown offset α , shown in Fig.




Fig. 3: Quantization Loss - Deterministic ISI Channel




Fig. 4: Offset Loss - Deterministic ISI Channel

4, is smaller than -0.6 dB for the considered range of offsets. In summary, the results show that for the wireless channel estimation task (82), a quantization level α close to zero is in general preferable and that the performance gap between the ideal and the 1-bit system increases with the SNR as well as with the offset value. Note that in the low SNR regime, the fact that the offset is known to the receiver does not provide additional accuracy when estimating the ISI channel θ .

3) *Performance Analysis - Hybrid Approach:* For the case of a random channel, we assume $\theta \sim \mathcal{N}(\mathbf{0}_M, \mathbf{R}_\theta)$, where $\mathbf{R}_\theta \in \mathbb{R}^{K \times K}$ is a diagonal matrix with k -th diagonal element $\sigma_{\theta_k}^2$. With the ideal receiver, the asymptotic performance of the MAP estimator can be characterized by the ECRLB (42)

$$\text{MSE}_y \stackrel{a}{=} \text{E}_\theta [\mathbf{F}^{-1}(\theta)] = \left(\sum_{n=1}^N \mathbf{X}_n \right)^{-1}. \quad (100)$$

For the 1-bit receiver, by plugging (87)-(89) into (46), one obtains the EHCRLB. The quantization losses from (52) and

(53) are given by

$$\chi(\alpha) \stackrel{a}{=} \sum_{k=1}^K \frac{\left[\left(\sum_{n=1}^N \mathbf{X}_n \right)^{-1} \right]_{kk}}{\left\{ \mathbf{E}_{\theta} \left[\left(\mathbf{J}_{\theta\theta}(\psi) - \frac{\mathbf{J}_{\theta\alpha}(\psi)\mathbf{J}_{\alpha\theta}(\psi)}{\mathbf{J}_{\alpha\alpha}(\psi)} \right)^{-1} \right] \right\}_{kk}}, \quad (101)$$

$$\chi^*(\alpha) \stackrel{a}{=} \sum_{k=1}^K \frac{\left[\left(\sum_{n=1}^N \mathbf{X}_n \right)^{-1} \right]_{kk}}{\left\{ \mathbf{E}_{\theta} \left[\mathbf{J}_{\theta\theta}^{-1}(\psi) \right] \right\}_{kk}}. \quad (102)$$

For low SNR, we identify that $\gamma = [\sigma_{\theta_1}^2 \dots \sigma_{\theta_K}^2]$ and $\gamma_0 = [0 \dots 0]$ to obtain the simplified expression

$$\begin{aligned} \lim_{\gamma \rightarrow \gamma_0} \text{MSE}_{\mathbf{z}}(\alpha) &\stackrel{a}{=} \lim_{\gamma \rightarrow \gamma_0} \text{MSE}_{\mathbf{z}}^*(\alpha) \\ &= \frac{1}{\phi_0(\alpha)} \left(\sum_{n=1}^N \mathbf{X}_n \right)^{-1}, \end{aligned} \quad (103)$$

by using (84) in (73).

4) *Results - Hybrid Approach:* For the parameterization of the hybrid ISI channel with $K = 3$, we use

$$\sigma_{\theta_k}^2 = \text{SNR}_k \quad (104)$$

and set the variances of the two interfering channel taps to $\text{SNR}_2 = \text{SNR}_1 - 3 \text{ dB}$ and $\text{SNR}_3 = \text{SNR}_1 - 6 \text{ dB}$. Fig.




Fig. 5: MSE - Hybrid ISI Channel (SNR = -21 dB)

5 shows the performance of the quantized receiver in a low SNR scenario (SNR = -21 dB) with and without knowledge of the hard-limiting offset from (49) and (39), respectively. As a reference, the performance of the ideal receive system (38) is also plotted. In Fig. 6 the RNMSE is depicted for a medium SNR setup (SNR = -3 dB). It can be observed that the analytic error formulas provide an accurate assessment of the behavior of the estimation algorithms in the ISI channel model. In Fig. 7 we explicitly sketch the quantization loss, while in Fig. 8 the accuracy degradation due to the estimation of the unknown offset is depicted. It can be observed that like in the deterministic case (Figs. 3 and 4), the loss due to the unknown threshold is small for the considered range of offsets.




Fig. 6: MSE - Hybrid ISI Channel (SNR = -3 dB)




Fig. 7: Quantization Loss - Hybrid ISI Channel




Fig. 8: Offset Loss - Hybrid ISI Channel

B. Single-tap Channel Estimation

For the special case of a single channel tap, i.e., $K = 1$, the derived expressions can be further simplified [46].

1) *Performance - Deterministic Approach:* For the deterministic case, with (84) we obtain

$$F(\theta) = N. \quad (105)$$

For the hard-limited receiver in (82), we have

$$\phi_n(\theta, \alpha) = \frac{\exp\left(-(\alpha - \theta x_n)^2\right)}{2\pi\left(Q(\alpha - \theta x_n) - Q^2(\alpha - \theta x_n)\right)}. \quad (106)$$

Therefore, using (87)-(89)

$$\begin{aligned} J_{\theta\theta}(\theta, \alpha) &= \sum_{n=1}^N \phi_n(\theta, \alpha) x_n^2 \\ &= \frac{N}{2} (\phi_+(\theta, \alpha) + \phi_-(\theta, \alpha)), \end{aligned} \quad (107)$$

$$\begin{aligned} J_{\theta\alpha}(\theta, \alpha) &= -\sum_{n=1}^N \phi_n(\theta, \alpha) x_n \\ &= -\frac{N}{2} (\phi_+(\theta, \alpha) - \phi_-(\theta, \alpha)), \end{aligned} \quad (108)$$

$$\begin{aligned} J_{\alpha\alpha}(\alpha) &= \sum_{n=1}^N \phi_n(\theta, \alpha) \\ &= \frac{N}{2} (\phi_+(\theta, \alpha) + \phi_-(\theta, \alpha)), \end{aligned} \quad (109)$$

where for brevity we define

$$\phi_+(\theta, \alpha) \triangleq \frac{\exp\left(-(\alpha + \theta)^2\right)}{2\pi\left(Q(\alpha + \theta) - Q^2(\alpha + \theta)\right)}, \quad (110)$$

$$\phi_-(\theta, \alpha) \triangleq \frac{\exp\left(-(\alpha - \theta)^2\right)}{2\pi\left(Q(\alpha - \theta) - Q^2(\alpha - \theta)\right)}. \quad (111)$$

Note, that the expressions (107)-(109) are due to the fact that with an equal symbol assignment each of the two BPSK signals is present for $\frac{N}{2}$ of the pilot symbols. Calculating the MSEs with (15), (22), and (34), we obtain

$$\text{MSE}_{\mathbf{y}}(\theta) \stackrel{a}{=} F^{-1}(\theta) = N^{-1} \quad (112)$$

and

$$\begin{aligned} \text{MSE}_{\mathbf{z}}(\theta, \alpha) &\stackrel{a}{=} \left(J_{\theta\theta}(\theta, \alpha) - \frac{J_{\theta\alpha}^2(\theta, \alpha)}{J_{\alpha\alpha}(\theta, \alpha)} \right)^{-1} \\ &= \frac{1}{2N} \frac{\phi_+(\theta, \alpha) + \phi_-(\theta, \alpha)}{\phi_+(\theta, \alpha)\phi_-(\theta, \alpha)}, \end{aligned} \quad (113)$$

$$\begin{aligned} \text{MSE}_{\mathbf{z}}^*(\theta, \alpha) &\stackrel{a}{=} J_{\theta\theta}^{-1}(\theta, \alpha) \\ &= \frac{1}{2N} (\phi_+(\theta, \alpha) + \phi_-(\theta, \alpha))^{-1}. \end{aligned} \quad (114)$$

When comparing both receivers corresponding to the data models in (77) and (82), the loss (35) is given by

$$\begin{aligned} \chi(\theta, \alpha) &\stackrel{a}{=} \frac{J_{\theta\theta}(\theta, \alpha)}{F(\theta)} - \frac{J_{\theta\alpha}^2(\theta, \alpha)}{J_{\alpha\alpha}(\theta, \alpha)F(\theta)} \\ &= 2 \frac{\phi_+(\theta, \alpha)\phi_-(\theta, \alpha)}{\phi_+(\theta, \alpha) + \phi_-(\theta, \alpha)}. \end{aligned} \quad (115)$$

Assuming that the offset is known in (82) and using (36) we obtain

$$\begin{aligned} \chi^*(\theta, \alpha) &\stackrel{a}{=} \frac{J_{\theta\theta}(\theta, \alpha)}{F(\theta)} \\ &= \frac{1}{2} (\phi_+(\theta, \alpha) + \phi_-(\theta, \alpha)), \end{aligned} \quad (116)$$

which, as predicted in (68), in the low SNR regime becomes

$$\lim_{\theta \rightarrow 0} \chi^*(\theta, \alpha) = \phi_0(\alpha). \quad (117)$$

As for a single channel parameter, i.e., $K = 1$, with (54)

$$\Upsilon(\theta, \alpha) = \frac{\text{MSE}_{\mathbf{z}}^*(\theta, \alpha)}{\text{MSE}_{\mathbf{z}}(\theta, \alpha)}, \quad (118)$$

the asymptotic loss due to the uncertainty in the hard-limiter offset α in the data model (82) is

$$\Upsilon(\theta, \alpha) \stackrel{a}{=} \frac{4\phi_+(\theta, \alpha)\phi_-(\theta, \alpha)}{(\phi_+(\theta, \alpha) + \phi_-(\theta, \alpha))^2}. \quad (119)$$

As $\phi_+(0, \alpha) = \phi_-(0, \alpha) = \phi_0(\alpha)$, according to (69), the loss (119) approaches 1 in low SNR scenarios.

In Fig. 9 the performance loss in (119) with respect to the unknown offset α is visualized. While in the low SNR regime the estimation of α has almost no effect onto the estimation of θ , the situation changes within the medium SNR regime. Here the fact that the threshold is unknown can have a significant effect on to the estimation accuracy when the offset α is too far from the symmetric case. Interestingly, when comparing to the multi-tap loss in Fig. 4 it can be observed that the loss for the single-tap case is much more pronounced. This is due to the fact that in the multi-tap channel the offset constitutes a significantly smaller portion of the parameter space Ψ .




Fig. 9: Offset Loss - Deterministic Single-Tap Channel

2) *Performance - Hybrid Approach:* In the case of a random channel parameter and $K = 1$, the asymptotic performance of the MAP estimator with the ideal receiver, can be characterized using the ECRLB from (42)

$$\text{MSE}_{\mathbf{y}} \stackrel{a}{=} \text{E}_{\theta} [F^{-1}(\theta)] = N^{-1}. \quad (120)$$

By plugging the expressions (107)-(109) into (46), for the 1-bit receiver, one obtains

$$\begin{aligned} \text{MSE}_z(\alpha) &\stackrel{a}{=} E_\theta \left[\frac{1}{2N} \frac{\phi_+(\theta, \alpha) + \phi_-(\theta, \alpha)}{\phi_+(\theta, \alpha)\phi_-(\theta, \alpha)} \right] \\ &= \frac{1}{2N} \left(E_\theta [\phi_-^{-1}(\theta, \alpha)] + E_\theta [\phi_+^{-1}(\theta, \alpha)] \right) \\ &= \frac{1}{N} E_\theta [\phi_+^{-1}(\theta, \alpha)], \end{aligned} \quad (121)$$

where the last step holds due to symmetry, i.e.,

$$E_\theta [\phi_-^{-1}(\theta, \alpha)] = E_\theta [\phi_+^{-1}(\theta, \alpha)]. \quad (122)$$

Under a known quantization threshold, we have

$$\text{MSE}_z^*(\alpha) \stackrel{a}{=} \frac{1}{2N} E_\theta \left[(\phi_+(\theta, \alpha) + \phi_-(\theta, \alpha))^{-1} \right], \quad (123)$$

such that the asymptotic quantization losses are

$$\chi(\alpha) \stackrel{a}{=} \frac{1}{E_\theta [\phi_+^{-1}(\theta, \alpha)]}, \quad (124)$$

$$\chi^*(\alpha) \stackrel{a}{=} \frac{2}{E_\theta \left[(\phi_+(\theta, \alpha) + \phi_-(\theta, \alpha))^{-1} \right]}. \quad (125)$$

For low SNR, we obtain the simplified expression

$$\lim_{\sigma_\theta^2 \rightarrow 0} E_\theta [\phi_+^{-1}(\theta, \alpha)] = \phi_0^{-1}(\alpha), \quad (126)$$

where the equality stems from the fact that the Gaussian density, parametrized by the continuous parameter σ_θ^2 forms a positive summability kernel [62, p. 9]. Hence, the asymptotic performance loss in the low SNR domain is given by

$$\lim_{\sigma_\theta^2 \rightarrow 0} \chi(\alpha) \stackrel{a}{=} \phi_0(\alpha), \quad (127)$$

such that the accuracy degradation due to the estimation of the unknown offset (54) is

$$\Upsilon(\alpha) \stackrel{a}{=} \frac{E_\theta \left[(\phi_+(\theta, \alpha) + \phi_-(\theta, \alpha))^{-1} \right]}{2 E_\theta [\phi_+^{-1}(\theta, \alpha)]}, \quad (128)$$

and vanishes in the low SNR regime, i.e.,

$$\lim_{\sigma_\theta^2 \rightarrow 0} \Upsilon(\alpha) \stackrel{a}{=} 1. \quad (129)$$

The accuracy degradation due to the unknown offset from (128) is visualized in Fig. 10. It shows that the offset estimation causes a significant additional error in the medium SNR regime while low SNR setups, as indicated by (129), the negative effect nearly vanishes. Also in the hybrid framework it can be observed that the single-tap offset loss (Fig. 10) is higher than in the multi-tap scenario (Fig. 8).

VI. CONCLUSION

In this paper, we have analyzed the problem of pilot-based channel parameter estimation from 1-bit quantized data with unknown hard-limiting threshold. In such a situation, in addition to the channel parameters, the receiver has to estimate the quantization level of the ADC. This in general has a negative impact on the achievable channel estimation accuracy. Providing a discussion for two different modeling




Fig. 10: Offset Loss - Hybrid Single-Tap Channel

approaches (deterministic and random channel parameters), we have shown that, under mild conditions on the channel model and the pilot signal, lack of offset knowledge does in general not degrade the performance in the low SNR regime. A similar conclusion seems to hold for medium SNR setups as long as the threshold of the 1-bit quantizer is close to the symmetric case. For the ISI channel estimation problem with multiple channel taps, it was observed that the estimation loss due to an unknown offset is in general small while in the single-tap scenario the degradation is more pronounced. In summary, our findings confirm that 1-bit A/D conversion is an interesting design option for future low-complexity wireless systems, in particular when the receiver is intended to solve complex channel estimation tasks in the low SNR regime. The presented results show that for such applications the requirements on the comparator circuit forming the low-complexity 1-bit ADC are minor. Deviations of the offset from the symmetric case can be compensated at small additional computational cost in the digital domain by appropriate estimation algorithms. For high-resolution statistical signal processing with 1-bit ADCs in the medium SNR regime our analysis shows that careful hardware design of the ADC is required, such that the comparator remains close to the symmetric case.

APPENDIX A

DERIVATION - FIM WITH 1-BIT ADC

Using the derivative (26) of the conditional probability mass function (6), we obtain

$$\begin{aligned} E_{z_n|\psi} \left[\left(\frac{\partial \ln p_{z_n}(z_n|\psi)}{\partial \theta} \right)^T \frac{\partial \ln p_{z_n}(z_n|\psi)}{\partial \theta} \right] &= \\ &= E_{z_n|\psi} \left[\frac{\exp \left(-(\alpha - s_n(\theta))^2 \right)}{2\pi Q^2 (z_n(\alpha - s_n(\theta)))} \left(\frac{\partial s_n(\theta)}{\partial \theta} \right)^T \frac{\partial s_n(\theta)}{\partial \theta} \right] \\ &= \frac{\exp \left(-(\alpha - s_n(\theta))^2 \right)}{2\pi} E_{z_n|\psi} \left[\frac{1}{Q^2 (z_n(\alpha - s_n(\theta)))} \right] \\ &\quad \cdot \left(\frac{\partial s_n(\theta)}{\partial \theta} \right)^T \frac{\partial s_n(\theta)}{\partial \theta} \end{aligned} \quad (130)$$

Further, with (6) and the Q-function property $Q(-\kappa) = 1 - Q(\kappa)$, $\kappa \in \mathbb{R}$, the expectation in (130) can be simplified

$$\begin{aligned} E_{z_n|\psi} \left[\frac{1}{Q^2(z_n(\alpha - s_n(\theta)))} \right] &= \\ &= \frac{Q(\alpha - s_n(\theta))}{Q^2(\alpha - s_n(\theta))} + \frac{Q(-(\alpha - s_n(\theta)))}{Q^2(-(\alpha - s_n(\theta)))} \\ &= \frac{1}{Q(\alpha - s_n(\theta))} + \frac{1}{1 - Q(\alpha - s_n(\theta))} \\ &= \frac{1}{Q(\alpha - s_n(\theta)) - Q^2(\alpha - s_n(\theta))}. \end{aligned} \quad (131)$$

With definition (27), (130) and (131) lead to the result (28).

APPENDIX B PROOF - THEOREM 1 (EHCRB)

Proof: Since the sequence of MLEs is asymptotically uniformly integrable, then [63]

$$\lim_{N \rightarrow \infty} \left| E_{z|\psi} \left[(\hat{\theta}_z(z) - \theta)(\hat{\theta}_z(z) - \theta)^T \right] - \left(J_{\theta\theta}(\psi) - \frac{J_{\theta\alpha}(\psi)J_{\alpha\theta}(\psi)}{J_{\alpha\alpha}(\psi)} \right)^{-1} \right| = 0. \quad (132)$$

Consequently, the total law of expectation implies that

$$\begin{aligned} \lim_{N \rightarrow \infty} \text{MSE}_z(\alpha) &= \\ &= \lim_{N \rightarrow \infty} E_\theta \left[E_{z|\psi} \left[(\hat{\theta}_z(z) - \theta)(\hat{\theta}_z(z) - \theta)^T \right] \right] \\ &= \lim_{N \rightarrow \infty} E_\theta \left[\left(J_{\theta\theta}(\psi) - \frac{J_{\theta\alpha}(\psi)J_{\alpha\theta}(\psi)}{J_{\alpha\alpha}(\psi)} \right)^{-1} \right]. \end{aligned} \quad (133)$$

■

REFERENCES

- [1] R. H. Walden, "Analog-to-digital converter survey and analysis," *IEEE J. Sel. Areas Commun.*, vol. 17, no. 4, pp. 539–550, Apr. 1999.
- [2] M. Verhelst and A. Bahai, "Where analog meets digital: Analog-to-information conversion and beyond," *IEEE Solid State Circuits Mag.*, vol. 7, no. 3, pp. 67–80, Sep. 2015.
- [3] J. M. Khoury, "On the design of constant settling time AGC circuits," *IEEE Trans. Circuits Syst. II, Analog Digit. Signal Process.*, vol. 45, no. 3, pp. 283–294, Mar. 1998.
- [4] G. Jacovitti and A. Neri, "Estimation of the autocorrelation function of complex Gaussian stationary processes by amplitude clipped signals," *IEEE Trans. Inf. Theory*, vol. 40, no. 1, pp. 239–245, Jan. 1994.
- [5] T. M. Lok and V. K. W. Wei, "Channel estimation with quantized observations," *IEEE Int. Symp. Inf. Theory*, pp. 333, Aug. 1998.
- [6] A. Host-Madsen and P. Handel, "Effects of sampling and quantization on single-tone frequency estimation," *IEEE Trans. Signal Process.*, vol. 48, no. 3, pp. 650–662, Mar. 2000.
- [7] O. Bar-Shalom and A. J. Weiss, "DOA estimation using one-bit quantized measurements," *IEEE Trans. Aerosp. Electron. Syst.*, vol. 38, no. 3, pp. 868–884, July 2002.
- [8] P. T. Boufounos and R. G. Baraniuk, "1-bit compressive sensing," in *42nd Annual Conference on Information Sciences and Systems (CISS)*, Princeton, NJ, 2008, pp. 16–21.
- [9] A. Mezghani, F. Antreich, and J. A. Nossek, "Multiple parameter estimation with quantized channel output," in *International ITG Workshop on Smart Antennas (WSA)*, Bremen, 2010, pp. 143–150.
- [10] O. Dabeer and U. Madhow, "Channel estimation with low-precision analog-to-digital conversion," in *IEEE International Conference on Communications (ICC)*, Cape Town, South Africa, 2010, pp. 1–6.
- [11] W. R. Bennett, "Spectra of quantized signals," *Bell Syst. Tech. J.*, vol. 27, pp. 446–472, 1948.
- [12] J. H. Van Vleck and D. Middleton, "The spectrum of clipped noise," *Proc. IEEE*, vol. 54, no. 1, pp. 2–19, Jan. 1966.
- [13] R. Curry, *Estimation and Control with Quantized Measurements*. M.I.T Press, 1970.
- [14] O. Dabeer, J. Singh, and U. Madhow, "On the limits of communication performance with one-bit analog-to-digital conversion," in *IEEE 7th Workshop on Signal Processing Advances in Wireless Communications (SPAWC)*, Cannes, 2006, pp. 1–5.
- [15] M. Ivrlač and J. A. Nossek, "On MIMO channel estimation with single-bit signal-quantization," presented at the International ITG Workshop on Smart Antennas (WSA), Vienna, 2007.
- [16] A. Mezghani and J. A. Nossek, "Capacity lower bound of MIMO channels with output quantization and correlated noise," presented at the IEEE International Symposium on Information Theory (ISIT), Cambridge, MA, 2012.
- [17] J. Mo and R. W. Heath, "Capacity analysis of one-bit quantized MIMO systems with transmitter channel state information," *IEEE Trans. Signal Process.*, vol. 63, no. 20, pp. 5498–5512, Oct. 2015.
- [18] S. Jacobsson, G. Durisi, M. Coldrey, U. Gustavsson, and C. Studer, "One-bit massive MIMO: Channel estimation and high-order modulations," in *IEEE International Conference on Communication Workshop (ICCW)*, London, 2015, pp. 1304–1309.
- [19] B. E. Boser and B. A. Wooley, "The design of sigma-delta modulation analog-to-digital converters," *IEEE J. Solid-State Circuits*, vol. 23, no. 6, pp. 1298–1308, Dec. 1988.
- [20] P. M. Aziz, H. V. Sorensen, and J. van der Spiegel, "An overview of sigma-delta converters," *IEEE Signal Process. Mag.*, vol. 13, no. 1, pp. 61–84, Jan. 1996.
- [21] E. N. Gilbert, "Increased information rate by oversampling," *IEEE Trans. Inf. Theory*, vol. 39, no. 6, pp. 1973–1976, Nov. 1993.
- [22] S. Shamai, "Information rates by oversampling the sign of a bandlimited process," *IEEE Trans. Inf. Theory*, vol. 40, no. 4, pp. 1230–1236, July 1994.
- [23] T. Koch and A. Lapidoth, "Increased capacity per unit-cost by oversampling," in *IEEE 26-th Convention of Electrical and Electronics Engineers in Israel*, Eliat, 2010, pp. 684–688.
- [24] S. Krone and G. Fettweis, "Capacity of communications channels with 1-bit quantization and oversampling at the receiver," in *35th IEEE Sarnoff Symposium (SARNOFF)*, Newark, NJ, 2012, pp. 1–7.
- [25] W. Zhang, "A general framework for transmission with transceiver distortion and some applications," *IEEE Trans. Comm.*, vol. 60, no. 2, pp. 384–399, Feb. 2012.
- [26] L. Landau and G. Fettweis, "Information rates employing 1-bit quantization and oversampling at the receiver," in *IEEE 15th International Workshop on Signal Processing Advances in Wireless Communications (SPAWC)*, Toronto, ON, 2014, pp. 219–223.
- [27] M. Stein and J. A. Nossek, "Will the 1-bit GNSS receiver prevail?," in *IEEE/ION Position, Location and Navigation Symposium (PLANS)*, Monterey, CA, 2014, pp. 1033–1040.
- [28] M. Stein, K. Barbé, and J. A. Nossek, "DOA parameter estimation with 1-bit quantization - Bounds, methods and the exponential replacement," in *20th International ITG Workshop on Smart Antennas*, Munich, Germany, 2016, pp. 1–6.
- [29] M. Stein, F. Wendler, A. Mezghani, and J. A. Nossek, "Quantization-loss reduction for signal parameter estimation," in *IEEE International Conference on Acoustics, Speech and Signal Processing*, Vancouver, BC, 2013, pp. 5800–5804.
- [30] M. Stein, S. Theiler, and J. A. Nossek, "Overdemodulation for high-performance receivers with low-resolution ADC," *IEEE Wireless Commun. Lett.*, vol. 4, no. 2, Apr. 2015.
- [31] M. Stein, A. Kürzl, A. Mezghani, and J. A. Nossek, "Asymptotic parameter tracking performance with measurement data of 1-bit resolution," *IEEE Trans. Signal Process.*, vol. 63, no. 22, pp. 6086–6095, Nov. 2015.
- [32] G. O. Balkan and S. Gezici, "CRLB based optimal noise enhanced parameter estimation using quantized observations," *IEEE Signal Process. Lett.*, vol. 17, no. 5, pp. 477–480, May 2010.
- [33] T. Koch and A. Lapidoth, "At low SNR, asymmetric quantizers are better," *IEEE Trans. Inf. Theory*, vol. 59, no. 9, pp. 5421–5445, Sept. 2013.

- [34] O. Dabeer and A. Karnik, "Signal parameter estimation using 1-bit dithered quantization," *IEEE Trans. Inf. Theory*, vol. 52, no.12, pp. 5389–5405, Dec. 2006.
- [35] O. Dabeer and E. Masry, "Multivariate signal parameter estimation under dependent noise from 1-bit dithered quantized data," *IEEE Trans. Inf. Theory*, vol. 54, no. 4, pp. 1637–1654, Apr. 2008.
- [36] G. Zeitler, G. Kramer, and A. C. Singer, "Bayesian parameter estimation using single-bit dithered quantization," *IEEE Trans. Signal Process.*, vol. 60, no. 6, pp. 2713–2726, June 2012.
- [37] N. Kurosawa, H. Kobayashi, K. Maruyama, H. Sugawara, and K. Kobayashi, "Explicit analysis of channel mismatch effects in time-interleaved ADC systems," *IEEE Trans. Circuits Syst. I, Fundam. Theory Appl.*, vol. 48, no. 3, pp. 261–271, Mar. 2001.
- [38] E. Chaumette, F. Vincent, J. Galy, and P. Larzabal, "On the influence of detection tests on deterministic parameters estimation," in *14th European Signal Processing Conference (EUSIPCO)*, Florence, 2006, pp. 1–5.
- [39] C. Ren, M. N. E. Korso, J. Galy, E. Chaumette, P. Larzabal, and A. Renaux, "On the accuracy and resolvability of vector parameter estimates," *IEEE Trans. Signal Process.*, vol. 62, no. 14, pp. 3682–3694, July 2014.
- [40] T. Menni, E. Chaumette, P. Larzabal, and J. P. Barbot, "New results on deterministic Cramér-Rao bounds for real and complex parameters," *IEEE Trans. Signal Process.*, vol. 60, no. 3, pp. 1032–1049, Mar. 2012.
- [41] Y. Rockah and P. M. Schultheiss, "Array shape calibration using sources in unknown locations—Part I: Far-field sources," *IEEE Trans. Acoust., Speech, Signal Process.*, vol. 35, no. 3, pp. 286–299, Mar. 1987.
- [42] I. Reuven and H. Messer, "A Barankin-type lower bound on the estimation error of a hybrid parameter vector," *IEEE Trans. on Inf. Theory*, vol. 43, no. 3, pp. 1084–1093, May 1997.
- [43] H. Messer, "The hybrid Cramér-Rao lower bound - From practice to theory," in *Fourth IEEE Workshop on Sensor Array and Multi-channel Processing (SAM)*, Waltham, MA, 2006, pp. 304–307.
- [44] Y. Noam and H. Messer, "Notes on the tightness of the hybrid Cramér-Rao lower bound," *IEEE Trans. Signal Process.*, vol. 57, no. 6, pp. 2074–2084, June 2009.
- [45] C. Ren, J. Galy, E. Chaumette, P. Larzabal, and A. Renaux, "Hybrid Barankin-Weiss-Weinstein bounds," *IEEE Signal Process. Lett.*, vol. 22, no. 11, pp. 2064–2068, Nov. 2015.
- [46] M. Stein, S. Bar, J. A. Nossek, and J. Tabrikian, "Performance analysis for pilot-based 1-bit channel estimation with unknown quantization threshold," in *IEEE International Conference on Acoustics, Speech and Signal Processing (ICASSP)*, Shanghai, 2016, pp. 4353–4357.
- [47] S. M. Kay, *Fundamentals of Statistical Signal Processing: Estimation Theory*. Prentice Hall, 1993.
- [48] C. R. Rao, "Information and accuracy attainable in the estimation of statistical parameters," *Bulletin of the Calcutta Mathematical Society*, vol. 37, no.3, pp. 81–91, 1945.
- [49] H. Cramér, *Mathematical Methods of Statistics*. Princeton, NJ: Princeton Univ. Press, 1946.
- [50] Y. Bar-Shalom, "On the asymptotic properties of the maximum-likelihood estimate obtained from dependent observations," *Journal of the Royal Statistical Society. Series B (Methodological)*, pp. 72–77, 1971.
- [51] B. R. Bhat, "On the method of maximum-likelihood for dependent observations," *Journal of the Royal Statistical Society. Series B (Methodological)*, vol. 36, no. 1, pp. 48–53, 1974.
- [52] S. D. Silvey, "A note on maximum-likelihood in the case of dependent random variables," *Journal of the Royal Statistical Society, Series B (Methodological)*, vol. 23, no. 2, pp. 444–452, 1961.
- [53] S. Bar and J. Tabrikian, "Bayesian estimation in the presence of deterministic nuisance parameters - Part II: Estimation methods," *IEEE Trans. Signal Process.*, vol. 63, no. 24, pp. 647–6658, Dec. 2015.
- [54] A. Yeredor, "The joint MAP-ML criterion and its relation to ML and to extended least-squares," *IEEE Trans. Signal Process.*, vol. 48, no.12, pp. 3484–3492, Dec. 2000.
- [55] J. Tabrikian and J. L. Krolík, "Theoretical performance limits on tropospheric refractivity estimation using point-to-point microwave measurements," *IEEE Trans. Antennas Propag.*, vol. 47, no. 11, pp. 1727–1734, Nov. 1999.
- [56] H. L. Van Trees and K. L. Bell, *Bayesian Bounds for Parameter Estimation and Nonlinear Filtering/Tracking*. Piscataway, NJ: Wiley-IEEE Press, 2007.
- [57] I. A. Ibragimov and R. Z. Hasminskii, *Statistical Estimation*. Springer, June 1981.
- [58] P. Jeganathan, "On the convergence of moments of statistical estimators," *Sankhyā: The Indian Journal of Statistics, Series A*, pp. 213–232, June 1982.
- [59] S. Bar and J. Tabrikian, "Bayesian estimation in the presence of deterministic nuisance parameters - Part I: Performance bounds," *IEEE Trans. Signal Process.*, vol. 63, no. 24, pp. 6632–6646, Dec. 2015.
- [60] G. H. Hardy and J. E. Littlewood, and G. Pólya, *Inequalities 2nd edition*. Cambridge University Press, 1988.
- [61] E. L. Lehmann and G. Casella, *Theory of Point Estimation*. Springer, 1998.
- [62] Y. Katznelson, *An Introduction to Harmonic Analysis 3rd edition*. Cambridge University Press, 2004.
- [63] A. W. van der Vaart, *Asymptotic Statistics*. Cambridge University Press, 1998.